



WYCOM SYSTEMS, INC.

800.869.0236 | Fax: 866.612.5236
www.Wycomsystems.com

PREMIER & OMNI

Blank Check Maker Interface (KEYBOARD:K,B)

The WYCOM UNIT can output a blank MICR check form without a signature using the Blank Check Maker Interface. To activate this feature, a keyboard must be connected to the Wycom and the Wycom unit must be turned on.

1. Set the executive switch KEYBOARD.
2. Select option "K Keyboard Checks"
3. Select option "B Blank Check Maker". The BLANK CHECK MAKER screen will appear.
4. The following screen will appear.

BLANK CHECK MAKER Position (1-8): Check Start # : Num Checks :

5. Enter the position number for the desired form ("Position (1-8):").
6. Enter the starting check number ("Check Start #:").
7. Enter the total number of checks desired (Num Checks:).
8. You will be prompted for a queue name. By default, "lp" will be displayed. This will send the print job to the output parallel port. You can select any other queue name that you have created using the web administration interface. For example, if you have created "raw1" using the Wycom web-based administration interface, then you could enter "raw1".
9. Press <ENTER> after the queue name, and WYCOM UNIT will generate the blank checks.

For example, suppose accounts payable was located at position #3, and you wanted to print checks 4001, 4002, 4003, and 4004. You would enter 3, 4001, and 4 in the data entry fields.

When printing more than one check type, the Wycom must be reset by either turning the Wycom key switch or by pressing ESC three times on the keyboard between check types. Both LEDs on the Wycom will flash indicating it has been reset.